

Tableau d'adressage des Systemes LEDTOLITE - 3 voies

Num CD	Adresses DMX	Code dip switch colordriver	Num CD	Adress DMX	Code dip switch colordriver	Num CD	Adress DMX	Code dip switch colordriver
1	1	00000001 0	62	184	010111000 0	123	367	101101111 0
2	4	000000100 0	63	187	010111011 0	124	370	101110010 0
3	7	000000111 0	64	190	010111110 0	125	373	101110101 0
4	10	000001010 0	65	193	011000001 0	126	376	101111000 0
5	13	000001101 0	66	196	011000100 0	127	379	101111011 0
6	16	000010000 0	67	199	011000111 0	128	382	101111110 0
7	19	000010011 0	68	202	011001010 0	129	385	110000001 0
8	22	000010110 0	69	205	011001101 0	130	388	110000100 0
9	25	000011001 0	70	208	011010000 0	131	391	110000111 0
10	28	000011100 0	71	211	011010011 0	132	394	110001010 0
11	31	000011111 0	72	214	011010110 0	133	397	110001101 0
12	34	000100010 0	73	217	011011001 0	134	400	110010000 0
13	37	000100101 0	74	220	011011100 0	135	403	110010011 0
14	40	000101000 0	75	223	011011111 0	136	406	110010110 0
15	43	000101011 0	76	226	011100010 0	137	409	110011001 0
16	46	000101110 0	77	229	011100101 0	138	412	110011100 0
17	49	000110001 0	78	232	011101000 0	139	415	110011111 0
18	52	000110100 0	79	235	011101011 0	140	418	110100010 0
19	55	000110111 0	80	238	011101110 0	141	421	110100101 0
20	58	000111010 0	81	241	011110001 0	142	424	110101000 0
21	61	000111101 0	82	244	011110100 0	143	427	110101011 0
22	64	001000000 0	83	247	011110111 0	144	430	110101110 0
23	67	001000011 0	84	250	011111010 0	145	433	110110001 0
24	70	001000110 0	85	253	011111101 0	146	436	110110100 0
25	73	001001001 0	86	256	100000000 0	147	439	110110111 0
26	76	001001100 0	87	259	100000011 0	148	442	110111010 0
27	79	001001111 0	88	262	100000110 0	149	445	110111101 0
28	82	001010010 0	89	265	100001001 0	150	448	111000000 0
29	85	001010101 0	90	268	100001100 0	151	451	111000011 0
30	88	001011000 0	91	271	100001111 0	152	454	111000110 0
31	91	001011011 0	92	274	100010010 0	153	457	111001001 0
32	94	001011110 0	93	277	100010101 0	154	460	111001100 0
33	97	001100001 0	94	280	100011000 0	155	463	111001111 0
34	100	001100100 0	95	283	100011011 0	156	466	111010010 0
35	103	001100111 0	96	286	100011110 0	157	469	111010101 0
36	106	001101010 0	97	289	100100001 0	158	472	111011000 0
37	109	001101101 0	98	292	100100100 0	159	475	111011011 0
38	112	001110000 0	99	295	100100111 0	160	478	111011110 0
39	115	001110011 0	100	298	100101010 0	161	481	111100001 0
40	118	001110110 0	101	301	100101101 0	162	484	111100100 0
41	121	001111001 0	102	304	100110000 0	163	487	111100111 0
42	124	001111100 0	103	307	100110011 0	164	490	111101010 0
43	127	001111111 0	104	310	100110110 0	165	493	111101101 0
44	130	010000010 0	105	313	100111001 0	166	496	111110000 0
45	133	010000101 0	106	316	100111100 0	167	499	111110011 0
46	136	010001000 0	107	319	100111111 0	168	502	111110110 0
47	139	010001011 0	108	322	101000010 0	169	505	111111001 0
48	142	010001110 0	109	325	101000101 0			
49	145	010010001 0	110	328	101001000 0			
50	148	010010100 0	111	331	101001011 0			
51	151	010010111 0	112	334	101001110 0			
52	154	010011010 0	113	337	101010001 0			
53	157	010011101 0	114	340	101010100 0			
54	160	010100000 0	115	343	101010111 0			
55	163	010100011 0	116	346	101011010 0			
56	166	010100110 0	117	349	101011101 0			
57	169	010101001 0	118	352	101100000 0			
58	172	010101100 0	119	355	101100011 0			
59	175	010101111 0	120	358	101100110 0			
60	178	010110010 0	121	361	101101001 0			
61	181	010110101 0	122	364	101101100 0			



www.ledtolite.com